


KST1623L3/L4/L5/L6/L7

Amplifier Transistor



1. Base 2. Emitter 3. Collector

NPN Epitaxial Silicon Transistor

Absolute Maximum Ratings T_a =25°C unless otherwise noted

Symbol	Parameter	Value	Units	
V_{CBO}	Collector-Base Voltage	50	V	
V _{CEO}	Collector-Emitter Voltage	40	V	
V_{EBO}	Emitter-Base Voltage	5.0	V	
I _C	Collector Current	100	mA	
P _C	Collector Dissipation	350	mW	
T _{STG}	Storage Temperature	150	°C	

Electrical Characteristics T_a =25°C unless otherwise noted

Symbol	Parameter	Test Condition	Min.	Max.	Units
I _{CBO}	Collector Cut-off Current	V _{CB} =40V, I _E =0		100	nA
I _{EBO}	Emitter Cut-off Current	V_{EB} =5V, I_{C} =0		100	nA
h _{FE}	DC Current Gain				
	: KST1623L3	V _{CE} =6V, I _C =1.0mA	60	120	
	: KST1623L4		90	180	
	: KST1623L5		135	270	
	: KST1623L6		200	400	
	: KST1623L7		300	600	
V _{CE} (sat)	Collector-Emitter Saturation Voltage	I _C =100mA, I _B =10mA		0.3	V
V _{BE} (sat)	Base-Emitter Saturation Voltage	I _C =100mA, I _B =10mA		1.0	V
V _{BE} (on)	Base-Emitter On Voltage	V _{CE} =6V, I _C =1.0mA	0.6	0.7	V
f _T	Current Gain Bandwidth Product	I _C =10mA, V _{CE} =6V, f=100MHz	200		MHz

MARKING CODE

Туре	KST1623L3	KST1623L4	KST1623L5	KST1623L6	KST1623L7
Mark	L3	L4	L5	L6	L7

Marking



Typical Characteristics




Figure 1. Static Characteristic




Figure 3. DC current Gain




Figure 5. Output Capacitance




Figure 2. Transfer Characteristic




Figure 4. Base-Emitter Saturation Voltage Collector-Emitter Saturation Voltage






Figure 6. Current Gain Bandwidth Product


©2000 Fairchild Semiconductor International Rev. A, February 2000

Package Demensions

SOT-23







Dimensions in Millimeters

TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

FACT™ QFET™ FACT Quiet Series™ QS™

FAST[®] Quiet Series[™] SuperSOT[™]-3 GTO[™] SuperSOT[™]-6

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

LIFE SUPPORT POLICY

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR INTERNATIONAL.

As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user.

2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

PRODUCT STATUS DEFINITIONS

Definition of Terms

Datasheet Identification	Product Status	Definition
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice in order to improve design.
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.

©2000 Fairchild Semiconductor International Rev. E